


TB-17 TIME SWITCH

■ OPERATION INSTRUCTIONS

Before operating this set, please adjust the selector located at the front left side of the body to the adequate frequency.



(1) Set the time-setting pins at the desired times

Push the time-setting pins onto the dial position indicating the selected time.

• To turn the load on, use a red pin.

To turn the load off, use a white pin.

Push the time-setting pin firmly into place.

(2) Set the present time

Turn the dial to the right in the direction of the arrow until the present time position on the dial is aligned with the present time arrow.

(3) Set the manual ON-OFF switch

Turn the manual ON-OFF switch to the right in the direction of the arrow to turn the load ON or OFF

(When the load is ON.)



(When the load is OFF.)



• When the load circuit continues ON or OFF for a long time, please operate manual ON-OFF switch after you have removed all time-setting pins.

• When the time-setting pin is within 1 hour of the present time, the manual ON-OFF switch should not be turned.

■ SPECIFICATIONS

Model No.	TB-17		
Movement type	AC-type		
Rated Voltage	110V	200-220V	240V
Voltage Tolerance	85-120V	170-240V	220-260V
Frequency	50/60Hz(selection type)		
Power Consumption	1.5W		
Time precision	Same as AC frequency		
Ambient Temperature	~10°C~+50°C		
Resistive Load	250VAC 15A		
Lamp Load	100VAC 1500W 200VAC 3000W		
Inductive Load	10A (cosφ=0.7 or more)		
Motor Load	100VAC 750W 200VAC 1500W		
Minimum setting unit	15 minute units		
Minimum setting interval	30 minutes		
No. of ON-OFF operations	Standard 6 operations Maximum, 48 operations are possible		
Weight	270g		