









DIGITAL COUNTER LH7 SERIES



<p>PICTURE</p> <p>SPECIFICATIONS</p>	 <p>HOUR COUNTER</p>				 <p>COUNTER</p>			
	ITEM NO.	LH7ET-6	LH7ET-8	LH7ET-6V	LH7ET-8V	LH7E-6	LH7E-8	LH7E-6V
COUNT INPUT	<ul style="list-style-type: none"> • CONTACT INPUT: BY SHORT CIRCUIT • CONTACT RESISTANCE: ≤ 10K Ω (ON) ≥ 500K Ω (OFF) 		<ul style="list-style-type: none"> • VOLTAGE INPUT: 4-30V DC 		<ul style="list-style-type: none"> • CONTACT INPUT: BY SHORT CIRCUIT • CONTACT RESISTANCE: ≤ 10K Ω (ON) ≥ 500K Ω (OFF) 		<ul style="list-style-type: none"> • VOLTAGE INPUT: 4-30V DC 	
NUMBER OF COUNTS	9999H59M	999999H59M	9999H59M	999999H59M	0-999999	0-99999999	0-999999	0-99999999
COUNTING SPEED	SIGNAL WIDTH : ≥ 1 SEC.				10 CPS (SIGNAL WIDTH : 50ms)			
RESET	SIGNAL WIDTH : ≥ 0.2 SEC.				VOLTAGE INPUT : 4-30V DC (SIGNAL WIDTH : ≥ 0.2 SEC.)			
CONNECTION DIAGRAM	 <p>COUNT INPUT : ① - ② RESET INPUT : ③ - ④</p>		 <p>COUNT INPUT : ① - ② RESET INPUT : ③ - ④</p>		 <p>COUNT INPUT : ① - ② RESET INPUT : ③ - ④</p>		 <p>COUNT INPUT : ① - ② RESET INPUT : ③ - ④</p>	
DIMENSIONS	<p>UNIT : mm</p> 